

## SERVER

The screenshot shows the 'Live1 Setup' dialog box with the 'Server' tab selected. The fields are filled with the following values: Profile: 'my icecast station', Server: 'server:8010', User: 'source', Password: 'passwd', Mount: 'live', and Stream name: 'groove radio'. Under the 'Protocol' section, the 'Icecast' radio button is selected. There are 'Test', 'OK', and 'Cancel' buttons at the bottom.

START SETUP IN YOUR PROGRAMS FOLDER

### Select page Server

### EXPLANATORY FIELDS AND BUTTONS

#### Profile

You can store up to 100 profiles for the webradio-server. In Live One you then have the ability to choose between them. You will see a drop-down list with all currently defined profiles and a profile called 'New' that enables you to add a new profile and 'Delete' that will delete the currently selected profile (if you have only 1 profile you can not delete that).

#### Server

The name of your internet radio server and port-number. In the common form: 'servername:portnr' for instance 'lucinl.com:9000'

#### User

Fill in the user-name you use to login at your server.

#### Password

Fill in the password belonging to your user name.

#### Mount

The mount-name, for icecast servers.

#### Stream name

The name of your radio-station.

#### Protocol

Shoutcast or Icecast.

#### Test

You can test your server-settings with this button. Luci live one will try to contact your server and login.

Go to adjust the next page or press OK to save and leave Setup.